

WHAT IS CLAIMED IS:

1 1. A method for demodulating data sequences in a
2 multiple access communication system, said method comprising
3 the steps of:

4 configuring a receiver to demodulate using an
5 interference cancellation demodulation scheme selected from
6 any of a plurality of interference cancellation demodulation
7 schemes; and

8 demodulating said data sequences according to said
9 interference cancellation demodulation scheme selected, said
10 demodulating comprising coupling said data sequences to an
11 interference cancellation unit (ICU) at instances based upon
12 the interference cancellation scheme selected.

1 2. The method according to claim 1, wherein said
2 interference cancellation demodulation scheme comprises a
3 successive interference cancellation demodulation scheme, a
4 parallel interference cancellation demodulation scheme, or
5 a hybrid interference cancellation demodulation scheme.

1 3. The method according to claim 1, wherein said step
2 of demodulating comprises utilizing the same processing
3 elements for any of the selected one of said plurality of
4 interference cancellation modulation schemes.

1 4. The method according to claim 1, wherein said step
2 of configuring further comprises the step of:
3 retrieving at least one parameter enabling said receiver
4 to function according to the interference cancellation
5 demodulation scheme selected.

1 5. The method according to claim 1, further comprising
2 the step of:
3 selectively storing certain demodulated data sequences
4 used in the interference cancellation demodulation for other
5 received data sequences.

1 6. The method according to claim 1, wherein said data
2 sequences are symbol sequences.

1 7. The method according to claim 1, wherein said step
2 of demodulating is repeated a plurality of times using only
3 ICU within said receiver so as to further cancel interference
4 influencing said data sequences.

1 8. The method according to claim 1, wherein said step
2 of coupling further comprises the step of:
3 generating a control signal for selectively activating
4 a switch disposed between said ICU and said data sequences,
5 said control signal being based upon said interference
6 cancellation demodulation scheme selected.

1 9. A receiver within a wireless communication system,
2 said receiver comprising:

3 a demodulator for demodulating data sequences appearing
4 at an input of the demodulator using an interference
5 cancellation demodulation scheme selected from any of a
6 plurality of interference cancellation demodulation schemes,
7 said demodulator comprising:

8 an ICU; and

9 a switch, coupled between said ICU and the input, said
10 switch being closed and opened during a demodulation
11 operation based upon the interference cancellation
12 demodulation scheme selected.

1 10. The receiver according to claim 9, wherein said
2 demodulator is configured by at least one parameter
3 associated with said receiver.

1 11. The receiver according to claim 9, wherein said ICU
2 is a single ICU.

1 12. The receiver according to claim 9, wherein for each
2 data sequence said ICU performs said interference
3 cancellation demodulation a plurality of times so as to
4 further cancel interference influencing said data sequences.

1 13. The receiver according to claim 12, wherein said
2 single ICU performs said selected interference cancellation
3 demodulation for a plurality of users.

1 14. The receiver according to claim 11, wherein the
2 switching time of said switch is controlled by at least one
3 parameter in said demodulator.

1 15. The receiver according to claim 11, wherein said
2 demodulator further comprises:

3 a second switch for selecting one of a plurality of user
4 codes, said one user code selected being provided to said
single ICU during said demodulation operation.

1 16. The receiver according to claim 9, wherein said
2 interference cancellation demodulation scheme is a successive
3 interference cancellation demodulation scheme, a parallel
4 interference cancellation demodulation scheme, or a hybrid
5 interference cancellation demodulation scheme.

1 17. The receiver according to claim 9, further
2 comprising:
3 a register, coupled between said ICU and said input, for
4 temporarily storing said data sequences.

1 18. The receiver according to claim 9, further
2 comprising:
3 accumulation registers for storing selected demodulated
4 data sequences.

1 19. The receiver according to claim 9, wherein said ICU
2 comprises:
3 a multiplier controlled to perform both despreading and
4 resspreading operations during the demodulation operation.

1 20. A method for demodulating a data sequence, said
2 method comprising:

3 identifying any one of a plurality of interference
4 cancellation demodulation schemes;

5 loading the data sequence in a first register;

6 transferring the data sequence within the first register
7 to a second register at predetermined time instances based
8 upon the interference cancellation demodulation scheme
9 identified;

10 despreading the data sequence in the second register
11 using a user code;

12 respreading the despread data sequence;

13 updating the first register based upon the respread data
14 sequence; and

15 after said despreading, selectively accumulating the
16 despread data sequences in an accumulator, the contents of
17 said accumulator comprising the demodulated data sequences.

1 21. The method according to claim 20, further
2 comprising:
3 repeating the steps of transferring, despreading,
4 respreading, updating and selectively accumulating, a
5 predetermined number of times.

1 22. An ICU for demodulating a data sequence, said ICU
2 comprising:

3 a first shift register containing a data sequence, and
4 a second shift register containing at least one code for a
5 user associated with said data sequence; and

6 a multiplier having inputs connected to outputs of said
7 first and said second shift registers, said multiplier
8 multiplying contents of said first and second shift
9 registers, whereby said first shift register, said second
10 shift register and said multiplier are controlled to perform
11 despread and respread operations.

1 23. The ICU according to claim 22, further comprising:

2 a switch adapted to select an operation performed by
3 said multiplier.

1 24. The ICU according to claim 22, further comprising:
2 an accumulator for accumulating the despread signal
3 generated by said multiplier, said accumulator connected to
4 the first shift register for supplying the despread signal
5 to said first shift register during a resspreading operation.

1 25. The ICU according to claim 22, wherein said second
2 shift register stores the user specific code used for the
3 despreading operation.

1 26. An interference cancellation method for canceling
2 the interference on a data sequence, said method comprising
3 the steps of:

4 receiving the data sequence;

5 detecting an estimate of a first spreading code's
6 symbols from said data sequence using an ICU;

7 storing the estimate of said first spreading code's
8 symbols in a first register associated with said first
9 spreading code's symbols; and

10 subtracting a first signal associated with the estimate
11 of said first spreading code's symbols from said data
12 sequence to produce a modified data sequence.

1 27. The interference cancellation method according to
2 claim 26, further comprising, prior to said step of
3 subtracting, the steps of:

4 detecting an estimate of a second spreading code's
5 symbols from said data sequence;

6 storing the estimate of said second spreading code's
7 symbols in a second register associated with said second

8 spreading code's symbols; and

9 wherein said step of subtracting further comprises
10 subtracting signals associated with the estimate of said
11 first spreading code's symbols and said second spreading
12 code's symbols from said data sequence to produce said
13 modified data sequence.

1 28. The interference cancellation method according to
2 claim 26, further comprising, after said step of subtracting,
3 the steps of:

4 detecting an estimate of a second spreading code's
5 symbols from said data sequence;

6 storing the estimate of said second spreading code's
7 symbols in a second register associated with said second
8 spreading code's symbols; and

9 subtracting a second signal associated with the estimate
10 of said second spreading code's symbols from said modified
11 data sequence.

1 29. The interference cancellation method according to
2 claim 26, further comprising the steps of:

3 a second detecting step for detecting the estimate of
4 said first spreading code's symbols from said modified data
5 sequence using said ICU;

6 accumulating the estimate of said second detecting step
7 of said first spreading code's symbols to said first register
8 associated with said first spreading code's symbols; and

9 subtracting a third signal associated with the estimate
10 of said second detection of said first spreading code's
11 symbols from said modified data sequence.

1 30. An interference cancellation system for canceling
2 interference on a data sequence, said system comprising:

3 a first register and a second register for temporarily
4 storing said data sequence;

5 a switch coupled between said first register and said
6 second register for transferring said data sequence from said
7 first register to said second register at predetermined time
8 intervals;

9 an ICU coupled to an output of said second register for
10 receiving the data sequence and detecting estimates of
11 spreading codes' symbols;

12 output registers for storing the estimates of said
13 spreading codes' symbols, each of said output registers being
14 associated with one of said spreading codes' symbols, said
15 output registers being adapted to accumulate subsequent
16 estimates of said spreading codes' symbols; and

17 subtraction means for subtracting signals associated
18 with the estimates of said spreading codes' symbols from said
19 data sequence, thereby removing the influence of the
20 estimates of said spreading codes' symbols from said data
21 sequence.

Patent Application
Docket #34645-00531USPT
Final Draft

1 31. The system according to claim 30, wherein said
2 signals associated with the estimates of said spreading
3 codes' symbols are respread versions of the estimates of said
4 spreading codes' symbols.

1
2
3
4
5
6
7
8
9
10
11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32
33
34
35
36
37
38
39
40
41
42
43
44
45
46
47
48
49
50
51
52
53
54
55
56
57
58
59
60
61
62
63
64
65
66
67
68
69
70
71
72
73
74
75
76
77
78
79
80
81
82
83
84
85
86
87
88
89
90
91
92
93
94
95
96
97
98
99
100
101
102
103
104
105
106
107
108
109
110
111
112
113
114
115
116
117
118
119
120
121
122
123
124
125
126
127
128
129
130
131
132
133
134
135
136
137
138
139
140
141
142
143
144
145
146
147
148
149
150
151
152
153
154
155
156
157
158
159
160
161
162
163
164
165
166
167
168
169
170
171
172
173
174
175
176
177
178
179
180
181
182
183
184
185
186
187
188
189
190
191
192
193
194
195
196
197
198
199
200
201
202
203
204
205
206
207
208
209
210
211
212
213
214
215
216
217
218
219
220
221
222
223
224
225
226
227
228
229
230
231
232
233
234
235
236
237
238
239
240
241
242
243
244
245
246
247
248
249
250
251
252
253
254
255
256
257
258
259
260
261
262
263
264
265
266
267
268
269
270
271
272
273
274
275
276
277
278
279
280
281
282
283
284
285
286
287
288
289
290
291
292
293
294
295
296
297
298
299
300
301
302
303
304
305
306
307
308
309
310
311
312
313
314
315
316
317
318
319
320
321
322
323
324
325
326
327
328
329
330
331
332
333
334
335
336
337
338
339
340
341
342
343
344
345
346
347
348
349
350
351
352
353
354
355
356
357
358
359
360
361
362
363
364
365
366
367
368
369
370
371
372
373
374
375
376
377
378
379
380
381
382
383
384
385
386
387
388
389
390
391
392
393
394
395
396
397
398
399
400
401
402
403
404
405
406
407
408
409
410
411
412
413
414
415
416
417
418
419
420
421
422
423
424
425
426
427
428
429
430
431
432
433
434
435
436
437
438
439
440
441
442
443
444
445
446
447
448
449
450
451
452
453
454
455
456
457
458
459
460
461
462
463
464
465
466
467
468
469
470
471
472
473
474
475
476
477
478
479
480
481
482
483
484
485
486
487
488
489
490
491
492
493
494
495
496
497
498
499
500
501
502
503
504
505
506
507
508
509
510
511
512
513
514
515
516
517
518
519
520
521
522
523
524
525
526
527
528
529
530
531
532
533
534
535
536
537
538
539
540
541
542
543
544
545
546
547
548
549
550
551
552
553
554
555
556
557
558
559
560
561
562
563
564
565
566
567
568
569
570
571
572
573
574
575
576
577
578
579
580
581
582
583
584
585
586
587
588
589
590
591
592
593
594
595
596
597
598
599
600
601
602
603
604
605
606
607
608
609
610
611
612
613
614
615
616
617
618
619
620
621
622
623
624
625
626
627
628
629
630
631
632
633
634
635
636
637
638
639
640
641
642
643
644
645
646
647
648
649
650
651
652
653
654
655
656
657
658
659
660
661
662
663
664
665
666
667
668
669
670
671
672
673
674
675
676
677
678
679
680
681
682
683
684
685
686
687
688
689
690
691
692
693
694
695
696
697
698
699
700
701
702
703
704
705
706
707
708
709
710
711
712
713
714
715
716
717
718
719
720
721
722
723
724
725
726
727
728
729
730
731
732
733
734
735
736
737
738
739
740
741
742
743
744
745
746
747
748
749
750
751
752
753
754
755
756
757
758
759
760
761
762
763
764
765
766
767
768
769
770
771
772
773
774
775
776
777
778
779
780
781
782
783
784
785
786
787
788
789
790
791
792
793
794
795
796
797
798
799
800
801
802
803
804
805
806
807
808
809
810
811
812
813
814
815
816
817
818
819
820
821
822
823
824
825
826
827
828
829
830
831
832
833
834
835
836
837
838
839
840
841
842
843
844
845
846
847
848
849
850
851
852
853
854
855
856
857
858
859
860
861
862
863
864
865
866
867
868
869
870
871
872
873
874
875
876
877
878
879
880
881
882
883
884
885
886
887
888
889
890
891
892
893
894
895
896
897
898
899
900
901
902
903
904
905
906
907
908
909
910
911
912
913
914
915
916
917
918
919
920
921
922
923
924
925
926
927
928
929
930
931
932
933
934
935
936
937
938
939
940
941
942
943
944
945
946
947
948
949
950
951
952
953
954
955
956
957
958
959
960
961
962
963
964
965
966
967
968
969
970
971
972
973
974
975
976
977
978
979
980
981
982
983
984
985
986
987
988
989
990
991
992
993
994
995
996
997
998
999
1000